



## Features

Convert battery power to household AC power installation.

- 2 x AC Outlets Allow You to Run Multiple Devices at The Same Time
- Runs Home Appliance, TVs , Power Tools and More
- Ideal For RVs, Boats, Trucks and Cabins
- USB Outlet Charges Tablets, Phones and Most Portable Electronics
- 400 Watt Continuous Output, 800 Watts Surge
- Compact Size



## SPECIFICATIONS

### AC OUTPUT

Power: 1500W (Continuous), 3000W(Peak)

Voltage / Current: 120 Vac / 12.5A

Frequency: 60±1Hz

Waveform: Modified sinewave

AC Outlet: 2 x 3Prong GFCI AC outlet

### DC OUTPUT

USB: 1 x 5V/750mA

### DC INPUT

Voltage (nominal): 12.5Vdc

Operation Range: 10.5-15.5Vdc / 140A

Material: ABS, Stell, Aluminum

### PROTECTION:

Input Undervoltage Warning: 11.0±0.3Vdc

Input Undervoltage Shutdown: 10.5±0.3Vdc

Input Undervoltage Recovery: 12.0±0.3Vdc

Input Overvoltage Shutdown: 15.5Vdc

Overload Shutdown: Yes

Output Short circuit Protection: Yes

Over Temperature Shutdown: Yes

## SHIPPING DETAILS

Item Number: 38215

UPC Code: 839290003060

Country of Origin: China / Hong Kong

Product Dimensions: 14.4 x 6.9 x 3.4 in

Color box Dimensions: 16.6 x 8.2 x 5.2 in

Product Weight: - lbs with package

- lbs without package

Master Quantity: -

Master Dimensions: - in

Master Weight: - lbs



**1-800-588-0590**

[www.naturepowerproducts.com](http://www.naturepowerproducts.com)



[fb.me/NaturePowerProducts](https://fb.me/NaturePowerProducts)

